



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223



sales@AHSystems.com

Fax: (818) 998-6892




www.AHSystems.com

BCP-514

Broadband Current Probe

10 KHz – 100 MHz

This current probe measures high power pulse currents such as those associated with EMP wave shapes. It clamps around large conductors or bundles of wire and has an aperture of 2.7".



Frequency Range: 10 KHz - 100 MHz

Transfer Impedance (dBΩ) -18 to 0

Max Cont. Current (Amps) 350

Connector: N-Type, Female

Physical Dimensions

Aperture: 2.7" (70 mm)

Diameter: 5.0" (125 mm)

Weight: 2.5 lb.'s (1.13 kg)

Features

- High current conducted emissions measurements without saturation.
- Ideally suited to measuring currents on large cables.
- Individually Calibrated (Transfer Impedance calibration included)
- Split Type Clamp-on Design
- Three Year Warranty

The BCP-514 measures high power pulse currents such as those associated with EMP wave shapes. This current probe is designed to clamp around large conductors or bundles of wire with an aperture of 2.7" (70 mm).

Recommended Accessories

- CPF-530 Current Probe Fixture
- SAC-213 N/N Cable, 3 Meter



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223
Fax: (818) 998-6892

◆ sales@AHSystems.com
◆ www.AHSystems.com



A.H. Systems, inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311
818.998.0223 fax 818.998.6892
info@AHSystems.com www.AHSystems.com



**Broadband Current Probe
Transfer Impedance
Model: BCP-514**

Transfer Impedance Conversion Formula:

$$\text{dB}\mu\text{A} = \text{dB}\mu\text{V} - \text{dB}\Omega + \text{cable loss}$$

